



2.2-5 Female to N Female Low PIM RF Adapter | 123-JFNF | 123e.com
Part Number: 123-JFNF

2.2-5 female to N female RF adapters are used to either change the gender from one connector type to another, to mate different connector types together, or as disposable interfaces for test and measurement applications where main launch cables need protection from wear and tear. 123eWireless RF adapters are designed for low loss with maximum mating cycles without degradation.

CROSS REFERENCE

Alternative To	TA-JFNF
----------------	---------

PHYSICAL SPECIFICATIONS

Connector A	2.2-5 Female
-------------	--------------

Connector B	N Female
-------------	----------

ELECTRICAL SPECIFICATIONS

Frequency Range	DC-8GHz
-----------------	---------

Impedance	50 ohm
-----------	--------

PIM	≤160dBc
-----	---------

VSWR	≤1.15 @3GHz, ≤1.25 @3GHz-6GHz
------	-------------------------------

ENVIRONMENTAL SPECIFICATIONS

Operating Temperature	-40°C to +155°C
-----------------------	-----------------

RoHS Compliance	Yes
-----------------	-----

Thank you visiting 123eWireless.

Please contact us at sales@123ewireless.com for any queries.