

4.3-10 Male to 2.2-5 Male RF Adapter | 123-HMJM | 123e.com
Part Number: 123-HMJM

4.3-10 male to 2.2-5 male Adapter RF coaxial adapter is used to change the gender from one connector type to another, to mate different connector types together or as a disposable interface for test and measurement applications where main launch cables need protection from wear and tear. 123eWireless RF adapters are designed for low loss with maximum mating cycles without degradation.

CROSS REFERENCE

Alternative To	C4467
----------------	-------

PHYSICAL SPECIFICATIONS

Mating Cycles	100
Connector A	4.3-10 Male
Connector B	2.2-5 Male

ELECTRICAL SPECIFICATIONS

Frequency Range	DC-6Ghz
Impedance	50 ohm
Insertion Loss	0.05dB
PIM	≤ -160 dBc
Return Loss	1.10 Max @4-6GHz

ENVIRONMENTAL SPECIFICATIONS

Operating Temperature	-55°C to +90°C
Weather Standard	IEC 60068 55/155/21

Thank you visiting 123eWireless.

Please contact us at sales@123ewireless.com for any queries.