

N male to QMA female RF Adapter | 123-NMQMAF | 123e.com
Part Number: 123-NMQMAF



N male to QMA female RF adapters are used to either change the gender from one connector type to another, to mate different connector types together, or as disposable interfaces for test and measurement applications.

CROSS REFERENCE

Alternative To

PHYSICAL SPECIFICATIONS

Mating Cycles	500
Connector A	N Male
Connector B	QMA Female
Insulation	PTFE

ELECTRICAL SPECIFICATIONS

Frequency Range	DC-8Ghz
Impedance	50 ohm
Insertion Loss	>0.1 dB
VSWR	1.15@ 6Ghz

ENVIRONMENTAL SPECIFICATIONS

Operating Temperature	-65 °C ~+85 °C
Weather Standard	IEC 60068 55/155/21

Thank you visiting 123eWireless.

Please contact us at sales@123ewireless.com for any queries.