



**N Male Right Angle to QMA Male Right Angle Low Loss 240 | 123-14NMRQMAR | 123e.com**

Part Number: 123-14NMRQMAR

N Male Right Angle to QMA Male Right Angle low loss 240 assembly, comparable to Times Microwave LMR®-240 50 Ohms coax cable. This RF jumper is UL listed indoor/outdoor riser rated GPS unit Jumper.

## CROSS REFERENCE

Alternative To

## PHYSICAL SPECIFICATIONS

|                 |                      |
|-----------------|----------------------|
| Connector A     | N Male Right Angle   |
| Connector B     | QMA Male Right Angle |
| Coax Cable Type | Low Loss 240         |
| Outer Diameter  | 0.24 (in)            |
| Jacket Color    | Black                |
| Jacket Material | PE - UV Resistant    |

## ELECTRICAL SPECIFICATIONS

|                 |              |
|-----------------|--------------|
| Frequency Range | 698-2200 MHz |
| Impedance       | 50 Ohm       |
| Return Loss     | -18db        |

## ENVIRONMENTAL SPECIFICATIONS

|                       |                |
|-----------------------|----------------|
| Operating Temperature | -40°C To +85°C |
| Weather Standard      | IP 67          |

Thank you visiting 123eWireless.

Please contact us at [sales@123ewireless.com](mailto:sales@123ewireless.com) for any queries.