



Din (7/16) female to Din (7/16) male RF adapter | 123-DFDM | 123e.com
Part Number: 123-DFDM

Din (7/16) female to Din (7/16) male RF adapters are passive Radio Frequency devices that have many purposes. RF adapters can be used to either change the gender from one connector type to another, to mate different connector types together, or can be used as disposable interfaces for test and measurement applications where main launch cables need protection from wear and tear. 123eWireless RF adapters are designed for low loss with maximum mating cycles without degradation.

CROSS REFERENCE

Alternative To	CA-DMDF
----------------	---------

PHYSICAL SPECIFICATIONS

Mating Cycles	500
Connector A	7/16 DIN FEMALE
Connector B	7/16 DIN MALE
Inner Conductor	Silver
Outer Conductor	Trimetal

ELECTRICAL SPECIFICATIONS

Frequency Range	DC-6GHz
Impedance	50 ohm
VSWR	≤1.04 @3GHz, ≤1.13 @-6GHz

ENVIRONMENTAL SPECIFICATIONS

Operating Temperature	-55°C to +85°C
Weather Standard	IEC 60068-1

Thank you visiting 123eWireless.

Please contact us at sales@123ewireless.com for any queries.