



4.1-9.5 Female to N Male RF Adapter | 123-MDFNM-P | 123e.com

Part Number: 123-MDFNM-P

4.1-9.5 Female to N male RF Adapters are used to either change the gender from one connector type to another, to mate different connector types together, or as disposable interfaces for test and measurement applications.

CROSS REFERENCE

Alternative To	RFN-1048-4, SM8224, PE91219, 1416
----------------	-----------------------------------

PHYSICAL SPECIFICATIONS

Mating Cycles	500
Connector A	4.1-9.5 Female
Connector B	N Male

ELECTRICAL SPECIFICATIONS

Frequency Range	DC-3GHz
Impedance	50 ohm
Insertion Loss	≤0.1dB
PIM	≤-160dBc
VSWR	≤1.10 @3GHz

Thank you visiting 123eWireless.

Please contact us at sales@123ewireless.com for any queries.